

Rocket RAID 2240 Controller SLES Linux Installation Guide

Version 1.0

Copyright © 2005 HighPoint Technologies, Inc.

All rights reserved.

Created on Jun 1, 2005

Table of Contents

1 Overview	1
2 Installing SLES Linux on RR2240 Controller.....	1
Step 1 Prepare Your Hardware for Installation.....	1
Step 2 Check System BIOS Settings.....	1
Step 3 Prepare the Driver Diskette.....	1
Step 4 Install SLES Linux.....	2
3 Installing RR2240 Driver on an Existing System.....	2
Step 1 Update Grub.....	2
Step 2 Install the Driver Module.....	2
Step 3 Test the Driver Module	3
Step 4 Configure System to Automatically Load the Driver.....	3
Step 5 Configure System to Mount Volumes when Startup	4
4 Updating the Driver	4
5 Installing RAID Management Software.....	4
6 Uninstalling.....	4

1 Overview

The purpose of this document is to provide clear instructions on how to install and use Rocket RAID 2240 Controller on SLES Linux system.

2 Installing SLES Linux on RR2240 Controller

If you would like to install SLES Linux onto drives attached to RR2240 controller, please perform the following operations:

Step 1 Prepare Your Hardware for Installation

After you attach your hard disks to RR2240 controller, you can use RR2240 BIOS Setting Utility to configure your hard disks as RAID arrays, or just use them as single disks.

Before installation, you must remove all the disk drives, which are not physically attached to RR2240 controller, from your system.

Note

If you have other SCSI adapters installed, you must make sure the RR2240 controller BIOS will be loaded firstly. If not, try to move it to another PCI slot. Otherwise you may be unable to boot up your system.

Step 2 Check System BIOS Settings

In your system BIOS SETUP menu, change **Boot Sequence** in such a way that the system will first boot from floppy or CDROM, and then from SCSI. Refer to your BIOS manual to see how to set boot sequence.

If your BIOS settings do not support such a boot sequence, you can first set it to boot from floppy or CDROM. After you finish installation, set SCSI as the first boot device to boot up the system.

Step 3 Prepare the Driver Diskette

The driver diskette is provided as an image file (slesdd.img).

On a DOS or Windows system, you can make the driver diskette using rawrite.exe. It can be found on the SLES Linux CD (under /dosutils). Just run it under a command window and follow its prompt.

On a Linux system, you can use the “dd” command to make the driver diskette. Insert a floppy disk into the floppy drive and type the command:

```
# dd if=slesdd.img of=/dev/fd0
```

Step 4 Install SLES Linux

- 1) Start installing by booting from SLES installation CD.
- 2) When CD boots, select "Installation" option and press F6 to load the driver.
- 3) Insert the Driver Disk when it displays "Please insert the Driver Update floppy".
- 4) When Diver Update Menu pop-up, press "OK" and "back" for back to installer.
- 5) Continue the installation as normal. You can refer to SLES Linux documents about OS installation.

Additional Installation Notes

The system device mapping order is the same as the order shown in RR2240 BIOS RAID Array view. If you have no other SCSI adapters installed, the first device will be /dev/sda. When creating mount points, you must mount /boot on /dev/sda.

3 Installing RR2240 Driver on an Existing System

If you are currently running Linux and would like to access drives or arrays attached to the Rocket RAID 2240 controller, you can perform the following steps.

Note

If you use a SCSI adapter to boot your system, you must make sure the RR2240 controller BIOS will be loaded after that adapter's BIOS. If not, try to move it to another PCI slot. Otherwise you may be unable to boot up your system.

Step 1 Update Grub

If you are running **SLES SMP System**, you must update /boot/grub/menu.lst first.

E.g.

```
default=0
timeout=8
title Linux
    kernel (hd0,1)/vmlinuz root=/dev/hda1 acpi=off
    initrd (hd0,1)/initrd
```

Then reboot the system to make new kernel parameter take effect.

Step 2 Install the Driver Module

The driver modules are packed in file **/linux/suse/[arch]-[version]/install/update.tar.gz** on the driver diskette. The following example shows how to extract the driver modules for SLES 9 from driver diskette:

```
# mount /dev/fd0 /media/floppy
# cd /
# tar xzf /media/floppy/linux/suse/i386-sles9/install/update.tar.gz
```

The driver modules will be extracted to directory
`/lib/modules/[kernel-ver]/kernel/drivers/scsi/`

Step 3 Test the Driver Module

You can test out the module to ensure that it works for your system by typing in the command "**insmod hptmv6.ko**".

Sometimes insmod will report "**unresolved symbols**" when you attempt to load the module. This can be caused by two ways:

- 1) The SCSI module is not loaded in kernel. Try to load SCSI modules first.

E.g.

```
# modprobe sd_mod
# insmod hptmv6.ko
```

- 2) You are using a kernel that is build off a different configuration with the driver. In this case the precompiled drivers cannot be used. You can build a driver for your kernel using the OpenSource package for RocketRAID 2240 controller.

To ensure the module has been loaded successfully, you can check the driver status by typing in the command "**cat /proc/scsi/hptmv6/x**", where x is the filename you found under `/proc/scsi/hptmv6/`. You should see the driver banner and a list of attached drives. You can now access the drives as a SCSI device (the first device is `/dev/sda`, then `/dev/sdb`, etc.).

Example

You have configured a RAID 1/0 array using 4 disks. It will be registered to system as device `/dev/sda`. You can use "**fdisk /dev/sda**" to create a partition on it, which will be `/dev/sda1`, and use "**mkfs /dev/sda1**" to setup a file system on the partition. Then you can mount `/dev/sda1` to somewhere to access it.

Step 4 Configure System to Automatically Load the Driver

Most likely, you will not want to type in "**insmod hptmv6**" each time you boot up the system. You can add the driver to the initial RAM disk image to load the driver at boot time:

- 1) Edit file `/etc/sysconfig/kernel` and add hptmv6 module to the line `INITRD_MODULES=...`, e.g:

```
INITRD_MODULES="reiserfs hptmv6"
```

- 2) Run depmod to update module configuration:

- ```
depmod
```
- 3) Run mkinitrd to update the initrd file:
- ```
# mkinitrd
```
- 4) If you are using lilo boot loader, run lilo again:
- ```
lilo
```

## Step 5 Configure System to Mount Volumes when Startup

Now you can inform the system to automatically mount the array by modifying the file `/etc/fstab`. E.g. You can add the following line to tell the system to mount `/dev/sda1` to location `/mnt/raid` after startup:

```
/dev/sda1 /mnt/raid ext2 defaults 0 0
```

## 4 Updating the Driver

To update the driver, simply reinstall the driver following the steps in previous section, "**Install RR2240 Driver on an Existing System**".

Replace the driver module `hptmv6.ko` in the `/lib/modules/[kernel-ver]/kernel/drivers/scsi/`. If the driver is loaded in `initrd` (e.g. when system is installed on the controller), you need to run `mkinitrd` to update the `initrd` file. Also, if you are using `lilo` boot loader, you need to run `lilo` again.

## 5 Installing RAID Management Software

HighPoint RAID Management Software is used to configure and keep track of your hard disks and RAID arrays attached to RR2240 controller. Installation of the management software is optional but recommended.

Please refer to HighPoint RAID Management Software documents about more information.

## 6 Uninstalling

You can only uninstall the driver when your system is not booting from devices attached to RR2240 controller. Just remove the lines you added to `/etc/modules.conf` and `/etc/fstab`.